

思科路由器口令破解执行总结 PDF转换可能丢失图片或格式
，建议阅读原文

https://www.100test.com/kao_ti2020/252/2021_2022_E6_80_9D_E7_A7_91_E8_B7_AF_E7_c101_252851.htm

1、启动路由器，在30秒那按ctrl break，进入rommon模式System Bootstrap, Version 12.1(3r)T2, RELEASE SOFTWARE (fc1)Copyright (c) 2000 by cisco Systems, Inc.C2600 platform with 65536 Kbytes of main memoryPC = 0xffff0ab6c, Vector = 0x500, SP = 0x80004884monitor: command "boot" aborted due to user interruptrommon 1 > 2、然后输入rommon 1 > confreg 0x2142You must reset or power cycle for new config to take effectrommon 2 > reset 3、路由器会重新启动System Bootstrap, Version 12.1(3r)T2, RELEASE SOFTWARE (fc1)Copyright (c) 2000 by cisco Systems, Inc.C2600 platform with 65536 Kbytes of main memoryprogram load complete, entry point: 0x80008000, size: 0x8a7f8cSelf decompressing the image :中间引导过程忽略。。。

。 。 --- System Configuration Dialog ---Would you like to enter the initial configuration dialog? [yes/no]: 4、按ctrl cPress RETURN to get started!Router>Router>enableRouter#copy startup-config running-configDestination filename [running-config]?816 bytes copied in 0.884 secsrouter1#router1#conf tEnter configuration commands, one per line. End with

CNTL/Z.router1(config)#router1(config)#enable secret ciscorouter1(config)#enable password 12345router1(config)#line con 0router1(config-line)#loginrouter1(config-line)#password ciscorouter1(config-line)#exitrouter1(config)#line aux

```
0router1(config-line)#loginrouter1(config-line)#password  
ciscorouter1(config-line)#exitrouter1(config)#line vty 0  
4router1(config-line)#loginrouter1(config-line)#password  
ciscorouter1(config-line)#exitrouter1(config)#config-register  
0x2102router1(config)#exitrouter1#router1#copy running-config  
startup-configDestination filename [startup-config]?Building  
configuration...[OK]router1# 100Test 下载频道开通，各类考试  
题目直接下载。 详细请访问 www.100test.com
```