

使用 h 协议访问 cisco 设备 PDF 转换可能丢失图片或格式，建议阅读原文

[https://www.100test.com/kao\\_ti2020/289/2021\\_2022\\_E4\\_BD\\_BF\\_E7\\_94\\_A8\\_h\\_E5\\_8D\\_c101\\_289645.htm](https://www.100test.com/kao_ti2020/289/2021_2022_E4_BD_BF_E7_94_A8_h_E5_8D_c101_289645.htm) SSH 协议要在 12.1 (11) 以上的 IOS 版本才被 cisco 设备支持的。查看 IOS 版本

```
Router#show version
Cisco IOS Software, 3600 Software
(C3640-JS-M), Version 12.4(10), RELEASE SOFTWARE (fc1)
Technical Support: http://www.cisco.com/techsupport
Copyright (c) 1986-2006 by Cisco Systems, Inc. Compiled Wed 16-Aug-06
04:04 by prod_rel_team
ROM: ROMMON Emulation Microcode
ROM: 3600 Software (C3640-JS-M), Version 12.4(10), RELEASE
SOFTWARE (fc1)
Router uptime is 11 minutes
System returned to
ROM by unknown reload cause - suspect
```

```
boot_data[BOOT_COUNT] 0x0, BOOT_COUNT 0,
BOOTDATA 19
System restarted at 19:05:39 UTC Wed Oct 24
2007
System image file is "tftp://255.255.255.255/unknown"
Cisco 3640 (R4700) processor (revision 0xFF) with 124928K/6144K bytes
of memory. Processor board ID 00000000 R4700 CPU at 100MHz,
Implementation 33, Rev 1.2 1 FastEthernet interface 4 Serial
interfaces
DRAM configuration is 64 bits wide with parity enabled.
125K bytes of NVRAM. 8192K bytes of processor board System
flash (Read/Write) Configuration register is 0x2102
下面开始正式
配置 SSH
ssh(config)#hostname ssh
ssh(config)#ip domain-name eric.com
ssh(config)#aaa new-model
ssh(config)#username eric86
password eric86
ssh(config)#crypto key generate rsa modulus 2048
The name for the keys will be: ssh.eric.com %
The key modulus size
```

is 2048 bits % Generating 2048 bit RSA keys, keys will be  
non-exportable...[OK] ssh(config)#line vty 0 15  
ssh(config-line)#transport input ssh ssh(config-line)#exit \*Oct 24  
19:26:06.595: %SSH-5-ENABLED: SSH 1.99 has been enabled 出于  
安全方面的原因,在对企业的cisco网络产品应该启用SSH并禁  
用TELNET.因为telnet是以明文方式传递口令的,而ssh不以明文  
方式传递口令,并且可以与radius和racacs 的方法一起使用.这样  
一来就可以大大的增加cisco设备的安全性.问题虽简单,但细节  
决定一切. 100Test 下载频道开通 , 各类考试题目直接下载。  
详细请访问 [www.100test.com](http://www.100test.com)