

如何建立拨号联接 PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/459/2021_2022__E5_A6_82_E4_BD_95_E5_BB_BA_E7_c97_459704.htm Public Const

```
RAS_MaxEntryName = 256 Private Type
```

```
RASENTRYNAME As
```

```
LongszEntryName(RAS_MaxEntryName) As ByteEnd Type
```

中 Char aa[16] 代表长度是16，可放 15个byte所以对应於vb便是 aa(15) as Byte如此才是长度16 (0--15)。故VB的宣告中不能再 用szEntryName(RAS_MaxEntryName 1)但

是Lenb(RASENTRYNAME)的长度却是 261 (4 257)，的确，这是vb的问题，而c的SizeOf传回的是4的倍数(32位元嘛)故值为264，所以我们计算某个Structure的长度时，要再多一些运算。以下的Fuction只适用於32位元的win95/ NT，以下在Form

```
中Private hConn as LongPrivate Sub Command1_Click()hConn = Dialup("我的连线", "user", "passwd")if hConn = 0
```

```
ThenDebug.Print "连线失败"end ifEnd SubPrivate Sub
```

```
Command2_Click()Call HangUp(hConn)End Sub
```

以下在.bas 中Option ExplicitPublic Const RAS_MaxEntryName = 256Public

```
Const RAS_MaxDeviceName = 128Public Const
```

```
RAS_MaxDeviceType = 16Public Const RAS_MaxPhoneNumber =
```

```
128Public Const RAS_MaxCallbackNumber = 128Public Const
```

```
UNLEN = 256Public Const PWLEN = 256Public Const DNLEN =
```

```
15Public Const ERROR_INVALID_HANDLE = 6Type
```

```
RASDIALPARAMS As Long
```

```
1052szEntryName(RAS_MaxEntryName) As
```

ByteszPhoneNumber(RAS_MaxPhoneNumber) As
ByteszCallbackNumber(RAS_MaxCallbackNumber) As
ByteszUserName(UNLEN) As ByteszPassword(PWLEN) As
ByteszDomain(DNLEN) As ByteEnd TypeType
RASCONNSTATUSdwSize As Long 144RasConnState As
LongdwError As LongszDeviceType(RAS_MaxDeviceType) As
ByteszDeviceName(RAS_MaxDeviceName) As ByteEnd
TypeDeclare Function RasGetErrorString Lib "rasapi32" _Alias
"RasGetErrorStringA" (ByVal ErrValue As Long, ByVal IpErrStr As
String, _ByVal cSize As Long) As LongDeclare Function RasDial Lib
"rasapi32" _Alias "RasDialA" (DialExt As Long, ByVal IpPhoneBook
As String, _RasDialParam As RASDIALPARAMS, ByVal
NotifyType As Long, _ByVal Notifier As Long, hRasConn As Long)
As LongDeclare Function RasHangUp Lib "rasapi32" Alias
_"RasHangUpA" (ByVal hRasConn As Long) As LongDeclare
Function RasGetConnectStatus Lib "rasapi32" Alias
_"RasGetConnectStatusA" (ByVal hRasConn As Long,
_lprasconnstatus As RASCONNSTATUS) As LongDeclare
Function RasGetEntryDialParams Lib "rasapi32" _Alias
"RasGetEntryDialParamsA" (ByVal lpszPhonebook As String,
_lpRasDialParams As RASDIALPARAMS, _lpfPassword As Byte)
As LongDeclare Sub Sleep Lib "kernel32" (ByVal dwMilliseconds As
Long) 100Test 下载频道开通，各类考试题目直接下载。详细
请访问 www.100test.com