

图解:交换机配置全接触(2) PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/142/2021_2022__E5_9B_BE_E8_A7_A3__E4_BA_A4_c101_142410.htm Catalyst 1900

Management Console Copyright (c) Cisco Systems, Inc.
1993 - 1999 All rights reserved. Standard Edition Software

Ethernet address : 00 - E0 - 1E - 7E - B4 - 40 PCA Number : 73
- 2239 - 01 PCA Serial Number : SAD01200001 Model Number
: WS - C1924 - A System Serial Number : FAA01200001 - -

- - - - -
- - - - - User Interface Menu [M] Menus /
/ 主配置菜单 [I] IP Configuration / / IP地址等配置 [P]
Console Password / / 控制密码配置 Enter Selection : / / 在此
输入要选择项的快捷字母，然后按回车键确认【注】“ / /
”后面的内容为笔者对前面语句的解释，下同。至此就正式
进入了交换机配置界面了，下面的工作就可以正式配置交换机了。

3、交换机的基本配置 进入配置界面后，如果是第一次配置，则首先要进行的就是IP地址配置，这主要是为后面进行远程配置而准备。IP地址配置方法如下：在前面所出现的配置界面“ Enter Selection : ”后中输入“ I ”字母，然后单击回车键，则出现如下配置信息： The IP Configuration Menu appears. Catalyst 1900 - IP Configuration Ethernet Address : 00 - E0 - 1E - 7E - B4 - 40 - - - - - Settings - - - - - [I] IP address [S] Subnet mask [G] Default gateway [B] Management Bridge Group [M] IP address of DNS server 1 [N] IP address of DNS

```
server 2 [ D ] Domain name [ R ] Use Routing Information
Protocol - - - - - Actions - - - - -
- - - - - [ P ] Ping [ C ] Clear cached
DNS entries [ X ] Exit to previous menu Enter Selection :
```

在以上配置界面最后的“ Enter Selection : ”后再次输入“ I ”字母，选择以上配置菜单中的“ IP address选项，配置交换机的IP地址，单击回车键后即出现如下所示配置界面 100Test 下载频道开通，各类考试题目直接下载。详细请访问 www.100test.com