

CCIE实验室考试指南(5) PDF转换可能丢失图片或格式，建议
阅读原文

https://www.100test.com/kao_ti2020/181/2021_2022_CCIE_E5_AE_9E_E9_AA_8C_c101_181762.htm Lab 05 -Frame Relay and

Appletalk Tunneling (Cayman) Given: The following diagram
Configure Router_B as a frame relay switch. Configure Appletalk with Cayman Tunneling. 此主题相关图片如下

```
: Solution: Router_C
Router_C#sh run
Building configuration...
Current configuration:
!
version 11.2
no service
password-encryption
no service udp-small-servers
no service tcp-small-servers
!
hostname Router_C
enable secret 5
...$1$jCQH$nzkhW6lQ9ywoAX87xsp9p1
enable password cnaprep
!
appletalk routing ipx routing 0060.09c3.df60
!
interface Loopback0
ip address 172.17.10.1 255.255.255.0
!
interface Tunnel0
no ip address
tunnel source Serial0
tunnel destination 172.16.10.1
tunnel mode cayman
!
interface Ethernet0
no ip address
appletalk cable-range 140-149
148.178
appletalk zone left
!
interface Ethernet1
no ip address
shutdown
!
interface Serial0
ip address 172.16.10.2 255.255.255.0
encapsulation frame-relay
no fair-queue
cdp enable
frame-relay lmi-type cisco
!
interface Serial1
no ip address
shutdown
!
no ip classless
!
line con 0
line aux 0
line vty 0 4
password sailing
login
!
end
Router_C#sh app route
Codes: R - RTMP derived, E - EIGRP derived, ...
C - connected, A - AURPS - static
P - proxy2 routes in internet
The first zone listed for each entry is its ...
default (primary) zone.
C Net 140-149 directly connected, Ethernet0, ...
zone left
R Net 150-159 [1/G] via 0.0, 4 sec, Tunnel0,
```

```
...zone rightRouter_Bversion 11.3no service
password-encryption!hostname Router_B!enable secret 5
...$1$eZ3D$vnTjKaCLtbSCcMF1mGzZm0enable password
cnaprep!ip host a 210.7.93.1ip host router_a 210.7.93.1ip host
router_c 65.62.245.2frame-relay switchingisdn switch-type
ntt!interface Serial0no ip addressno ip mroute-cacheshutdownno
fair-queueclockrate 4000000!interface Serial1ip address 65.62.245.3
255.255.255.0encapsulation frame-relayno ip mroute-cachekeepalive
15clockrate 2000000frame-relay lmi-type ciscoframe-relay intf-type
dceframe-relay route 100 interface Serial2 ...200!interface Serial2ip
address 65.62.245.4 255.255.255.0encapsulation frame-relayno ip
mroute-cachekeepalive 15clockrate 115200frame-relay lmi-type
ciscoframe-relay intf-type dceframe-relay route 200 interface Serial1
...100!interface Serial3no ip addressno ip mroute-cacheshutdownno
cdp enable!interface TokenRing0no ip addressno ip
mroute-cacheshutdownno cdp enable!interface BRI0no ip
addressno ip mroute-cacheshutdownno cdp enable!ip classless!!line
con 0exec-timeout 0 0line aux 0line vty 0 4password
ccieprelogin!endRouter_ARouter_A#sh runBuilding
configuration...Current configuration:!!version 11.3no service
password-encryption!hostname Router_A!enable secret 5
...$1$.s1R$iaEqZxLnYJo2QIZi8UNaO0enable password
ccnaprepappletalk routingipx routing 0010.7b15.bd41!interface
Loopback0ip address 172.17.10.2 255.255.255.0!interface Tunnel0no
ip addressstunnel source Serial0/0tunnel destination
172.16.10.2tunnel mode cayman!interface Ethernet0/0ip address
```

```
172.18.10.2 255.255.255.0no ip mroute-cacheappletalk cable-range
150-159 ...152.202appletalk zone rightno cdp enable!interface
Serial0/0ip address 172.16.10.1 255.255.255.0encapsulation
frame-relayno ip mroute-cachecdp enableframe-relay lmi-type
cisco!interface TokenRing0/0no ip addressno ip
mroute-cacheshutdownring-speed 16no cdp enable!interface
FastEthernet1/0no ip addressno ip mroute-cacheshutdownno cdp
enable!ip classless!line con 0exec-timeout 0 0line aux 0line vty 0
4password ccieprelogin!endRouter_A#sh app routeCodes: R -
RTMP derived, E - EIGRP derived, ...C - connected, A - AURPS -
static P - proxy2 routes in internetThe first zone listed for each entry
is its ...default (primary) zone.R Net 140-149 [1/G] via 0.0, 7 sec,
Tunnel0, ...zone leftC Net 150-159 directly connected,
...Ethernet0/0, zone rightNotice that, when using Cayman tunneling,
you must not configurethe tunnel with an AppleTalk network
address.When configuring GRE-IP, an Appletalk address must be
used. 100Test 下载频道开通 , 各类考试题目直接下载。详细请
访问 www.100test.com
```