

使用Xmodem恢复IOS方法 PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/237/2021_2022_E4_BD_BF_E7_94_A8Xmod_c101_237149.htm 如果你不小心使用了命令erase flash 那么发生什么就可想而知了。因此，建议在你拿到路由器等网络设备时 最好先将它的IOS等操作系统备份出来，以备万一！ 本篇主要介绍通过Xmodem上传IOS的过程（以Cisco 2610为例，不过这个方法用在其他设备上没什么太大区别）准备工作，只要有Cisco原配的线缆就可以（注：Xmodem与实际的modem没有任何联系 只是一个传输协议 数据是通过终端的串口和路由器的Console口灌进去的） 在没有IOS的情况下 系统只能进入Rommon状态，在这个状态下只能见到如下命令： rommon 8 > ?alias set and display aliases commandboot boot up an external processbreak set/show/clear the breakpointconfreg configuration register utilitycont continue executing a downloaded imagecontext display the context of a loaded imagecookie display contents of cookie PROM in hexdev list the device tabledir list files in file systemdis display instruction streamdnld serial download a program moduleframe print out a Oselected stack framehelp monitor builtin command helphistory monitor command historymeminfo main memory informationrepeat repeat a monitor commandreset system resetset display the monitor variablesstack produce a stack tracesync write monitor environment to NVRAMsysret print out info from last system returnftpdnld tftp image downloadunalias unset an aliasunset unset a monitor variablexmodem x/ymodem image download在这

个模式下，输入Xmodemrommon 9 > xmodem会提示如下警告：
: WARNING: All existing data in bootflash will be lost! Invoke this application only for disaster recovery. Do you wish to continue? y/n
[n]: y Ready to receive file ? ... 然后在超级终端的传送栏目=> 选择发送选项 => 再选择Xmodem 并指明IOS所在的路径即开始上传IOS，等待时间很长，视IOS的大小和传输速度。对于初次做IOS上传，建议不要去修改什么传输速率。传完以后 对整个系统初始化 界面如下：Erasing flash at 0x603c0000 program flash location 0x602f0000 Download Complete! program load complete, entry point: 0x80008000, size: 0x2f0074 Self decompressing the image :

```
#####
#####
```

[OK] Restricted Rights Legend Use, duplication, or disclosure by the Government is subject to restrictions as set forth in subparagraph(c) of the Commercial Computer Software - Restricted Rights clause at FAR sec. 52.227-19 and subparagraph(c) (1) (ii) of the Rights in Technical Data and Computer Software clause at DFARS sec. 252.227-7013.

cisco Systems, Inc. 170 West Tasman Drive San Jose, California 95134-1706

Cisco Internetwork Operating System Software IOS (tm) C2600 Software (C2600-I-M), Version 11.3(6)T, RELEASE SOFTWARE (fc1)

Copyright (c) 1986-1998 by cisco Systems, Inc.

Compiled Tue 06-Oct-98 18:42 by ccail Image text-base:

0x80008084, data-base: 0x80554578cisco 2610 (MPC860) processor
(revision 0x202) with 12288K/4096K bytes of memory.Processor
board ID JAB0233005Z (3677578902)M860 processor: part number
0, mask 32Bridging software.X.25 software, Version 3.0.0.1
Ethernet/IEEE 802.3 interface(s)1 Serial network interface(s)32K
bytes of non-volatile configuration memory.4096K bytes of
processor board System flash (Read/Write)Press RETURN to get
started!00:00:06: %LINK-3-UPDOWN: Interface Ethernet0/0,
changed state to up00:00:06: %LINK-3-UPDOWN: Interface
Serial0/0, changed state to up00:00:06: %SYS-5-CONFIG_I:
Configured from memory by console00:00:06: %SYS-5-RESTART:
System restarted --Cisco Internetwork Operating System
SoftwareIOS (tm) C2600 Software (C2600-I-M), Version 11.3(6)T,
RELEASE SOFTWARE (fc1)Copyright (c) 1986-1998 by cisco
Systems, Inc.Compiled Tue 06-Oct-98 18:42 by ccai00:00:07:
%LINEPROTO-5-UPDOWN: Line protocol
onWL_bank_2610_2>Interface Ethernet0/0, changed state to
up00:00:07: %LINEPROTO-5-UPDOWN: Line protocol on
Interface Serial0/0, changed state to up00:00:07:
%LINEPROTO-5-UPDOWN: Line protocol on Interface
Loopback0, changed state to up2610_2> 100Test 下载频道开通 ,
各类考试题目直接下载。 详细请访问 www.100test.com