

[Cisco抗DDoS设备]升级Detector_Guard总结 PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/461/2021_2022__5BCisco_E6_8A_97D_c101_461706.htm

guard-5.1-6.0.i386detector-5.1-6.0.i3861. 备份detector的配置copy

[zone zone-name] running-config ftp server full-file-name [login

[password]]copy running-config ftp server full-file-name [login

[password]]配置导回detector: deactivate当前zone, 当前配置将被

取代copy ftp running-config server full-file-name [login

[password]]2. 导出所有zone的攻击报告copy reports [details]

[xml] ftp server full-file-name [login] [password]3. 导出Zone

reportcopy zone zone-name reports [current | report-id] [xml]

[details] ftp server full-file-name [login] [password] 4. 导出Log文

件copy [zone zone-name] log ftp server full-file-name [login

[password]]5. 导出packet-dump capture文件, 本次没有copy zone

zone-name packet-dump captures [capture-name] ftp server

remote-path [login [password]]6. 下载os软件到ftp server7. 在设备

上执行copy ftp new-version /server-ipaddress/ fullfile-name/ login/

password/8. copy完毕后 , deactivate zone后 , 执行install

new-version如 : user@DETECTOR# copy ftp new-version

10.0.0.191 /home/Versions/R3.i386.rpm user FTP in

progress...user@DETECTOR# install new-version9. show version检

查10. burning a New Flash Version 如果需要Bad CFE version (X).

This version requires version Y执行命令 : falsh-burn / reload

100Test 下载频道开通 , 各类考试题目直接下载。 详细请访问

www.100test.com