

微软认证辅导:linux下远程控制windows系统 PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/644/2021_2022_E5_BE_AE_E8_BD_AF_E8_AE_A4_E8_c100_644669.htm 在实际工作中，桌面系统用的最多还是Windows，怎么在Linux桌面远程控制Windows系统呢。现在通过rdesktop软件就能方便的远程控制。。。首先我们要安装这个软件。我的linux系统：Redhat enterprise linux 5 下面我们来安装rdesktop软件：
[root@Wang Server]# rpm -ivh rdesktop-1.4.1-4.i386.rpm
[root@Wang Server]# rdesktop --help
rdesktop: invalid option -- -
rdesktop: A Remote Desktop Protocol client. Version 1.4.1. Copyright (C) 1999-2005 Matt Chapman. See <http://www.rdesktop.org/> for more information. Usage: rdesktop [options] server[:port] -u: user name -d: domain -s: shell -c: working directory -p: password (- to prompt) -n: client hostname -k: keyboard layout on server (en-us, de, sv, etc.) -g: desktop geometry (WxH) -f: full-screen mode 连接后是否显示全屏 -b: force bitmap updates -L: local codepage -B: use BackingStore of X-server (if available) -e: disable encryption (French TS) -E: disable encryption from client to server -m: do not send motion events -C: use private colour map -D: hide window manager decorations -K: keep window manager key bindings -S: caption button size (single application mode) -T: window title -N: enable numlock synchronization -X: embed into another window with a given id. -a: connection colour depth 连接后显示的位色，比如有8位色，16位色，24位色 -z: enable rdp compression -x: RDP5 experience (m[odem 28.8], b[roadband], l[an] or hex nr.) -P: use

persistent bitmap caching -r: enable specified device redirection (this flag can be repeated) -r comport:COM1=/dev/ttyS0: enable serial redirection of /dev/ttyS0 to COM1 or
COM1=/dev/ttyS0,COM2=/dev/ttyS1 -r disk:floppy=/mnt/floppy:
enable redirection of /mnt/floppy to floppy share or
floppy=/mnt/floppy,cdrom=/mnt/cdrom -r clientname=: Set the
client name displayed for redirected disks -r lptport:LPT1=/dev/lp0:
enable parallel redirection of /dev/lp0 to LPT1 or
LPT1=/dev/lp0,LPT2=/dev/lp1 -r printer:mydeskjet: enable printer
redirection or mydeskjet="HP LaserJet IIIP" to enter server driver as
well -r sound:[local|off|remote]: enable sound redirection remote
would leave sound on server -0: attach to console -4: use RDP
version 4 -5: use RDP version 5 (default) [root@Wang Server]#
rdesktop -u administrator 192.168.0.196 现在已经成功连接
到192.168.0.196那台机子上。更多优质资料尽在百考试题论坛
百考试题在线题库 #0000ff>微软认证更多详细资料 100Test 下
载频道开通，各类考试题目直接下载。详细请访问
www.100test.com