

6台2501做FR-SwitchFullmesh配置 PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/260/2021_2022_6_E5_8F_B02501_E5_81_c101_260718.htm 6台2501，总共有12个串口，给另外6台路由器做Frame-Switch用，通过FR over GRE配置，VC

为Full Mesh.最近应备考CCIE朋友要求，写配置如下，供参考

```
：基本配置：FR1:no ip domain-loline vty 0 4no loginenable
secret one-tom.comhost FR1frame switchint e0ip addr 99.1.1.1
255.255.255.0no shutint tu2tu sou e0tu des 99.1.1.2int tu3tu sou e0tu
des 99.1.1.3int tu4tu sou e0tu des 99.1.1.4int tu5tu sou e0tu des
99.1.1.5int tu6tu sou e0tu des 99.1.1.6int s0en frclock rate 64000no
shframe lmi-ty ansiframe intf dceint s1en frclock rate 64000no
shframe lmi-ty ansiframe intf dce FR2no ip domain-loline vty 0 4no
loginenable secret one-tom.comframe switchhost FR2int e0ip addr
99.1.1.2 255.255.255.0no shutint tu1tu sou e0tu des 99.1.1.1int tu3tu
sou e0tu des 99.1.1.3int tu4tu sou e0tu des 99.1.1.4int tu5tu sou e0tu
des 99.1.1.5int tu6tu sou e0tu des 99.1.1.6int s0en frclock rate
64000no shframe lmi-ty ansiframe intf dceint s1en frclock rate
64000no shframe lmi-ty ansiframe intf dce FR3no ip domain-loline
vty 0 4no loginenable secret one-tom.comhost FR3frame switchint
e0ip addr 99.1.1.3 255.255.255.0no shutint tu1tu sou e0tu des
99.1.1.1int tu2tu sou e0tu des 99.1.1.2int tu4tu sou e0tu des
99.1.1.4int tu5tu sou e0tu des 99.1.1.5int tu6tu sou e0tu des
99.1.1.6int s0en frclock rate 64000no shframe lmi-ty ansi 需要什么
来搜一搜吧so.bitsCN.comframe intf dceint s1en frclock rate
64000no shframe lmi-ty ansiframe intf dce FR4no ip domain-loline
```

```
vty 0 4no loginenable secret one-tom.comhost FR4frame switchint
e0ip addr 99.1.1.4 255.255.255.0no shutint tu1tu sou e0tu des
99.1.1.1int tu2tu sou e0tu des 99.1.1.2int tu3tu sou e0tu des
99.1.1.3int tu5tu sou e0tu des 99.1.1.5int tu6tu sou e0tu des
99.1.1.6int s0en frclock rate 64000no shframe lmi-ty ansiframe intf
dceint s1en frclock rate 64000no shframe lmi-ty ansiframe intf dce
FR5no ip domain-loline vty 0 4no loginenable secret
one-tom.comhost FR5frame switchint e0ip addr 99.1.1.5
255.255.255.0no shutint tu1tu sou e0tu des 99.1.1.1int tu2tu sou e0tu
des 99.1.1.2int tu3tu sou e0tu des 99.1.1.3int tu4tu sou e0tu des
99.1.1.4int tu6tu sou e0tu des 99.1.1.6int s0en frclock rate 64000no
shframe lmi-ty ansiframe intf dceint s1en frclock rate 64000no
shframe lmi-ty ansiframe intf dce FR6no ip domain-loline vty 0 4no
loginenable secret one-tom.comhost FR6frame switchint e0ip addr
99.1.1.6 255.255.255.0no shutint tu1tu sou e0tu des 99.1.1.1int tu2tu
sou e0tu des 99.1.1.2int tu3tu sou e0tu des 99.1.1.3int tu4tu sou e0tu
des 99.1.1.4int tu5tu sou e0tu des 99.1.1.5int s0en frclock rate
64000no shframe lmi-ty ansiframe intf dceint s1en frclock rate 64000
bitsCN_net中国网管博客no shframe lmi-ty ansiframe intf dce
100Test 下载频道开通，各类考试题目直接下载。详细请访问
www.100test.com
```