

在索尼爱立信JP7平台上自动启动MIDlet PDF转换可能丢失图片或格式，建议阅读原文

https://www.100test.com/kao_ti2020/167/2021_2022__E5_9C_A8_E7_B4_A2_E5_B0_BC_E7_c104_167345.htm 开机就能自动启动MIDlet一直是J2ME开发者的梦想，这一梦想在索尼爱立信的JP7平台上实现了。不过需要注意的是早期的几款机型不支持，比如K790等。具体请参考索尼爱立信的手册。开机自启动功能是通过Push注册来完成的，因此可以使用两种方式注册。第一种通过在jad文件注明PUSH注册的方式即可，如下。

```
//MIDlet-Push-: , MIDlet-Push-1: autostart://: ,
AutoStartStatic, *请注意URL的写法是autostart://: 如果想动态注册，可以通过下面的方法。
//Registers the pushRegistry
public void Register(){ // List of registered push connections. String
connections[]. // Check to see if the connection has been registered.
// This is a dynamic connection allocated on first // time execution of
this MIDlet. connections = PushRegistry.listConnections(false). if
(connections.length == 0) { try { //Register so the MIDlet will wake
up when phone is started.
PushRegistry.registerConnection("autostart://:", "AutoStartDyn",
"*"). sDisplayString = "MIDlet is registered". } catch (Exception ex) {
System.out.println("Exception: " ex). sDisplayString = "Fail: " ex. } }
else { sDisplayString = "Already registered". }
displayForm.deleteAll().
displayForm.append(sDisplayString).}
//Unregisters the
pushRegistry
public void Unregister(){ if
(PushRegistry.unregisterConnection("autostart://:")){
```

```
System.out.println("The pushRegistry is unregistered").  
sDisplayString = "MIDlet is unregistered.". }else{  
System.out.println("There is no pushRegistry to unregister").  
sDisplayString = "No MIDlet to unregister or failed to unregister". }  
displayForm.deleteAll(). displayForm.append(sDisplayString).}
```

由于手头没有SonyEricsson JP7平台的手机，因此没有办法测试
开机自动启动功能。有条件的可以自己测试一下。 100Test 下
载频道开通，各类考试题目直接下载。详细请访问
www.100test.com